



# Control Center IndigoUltra®




Your security solution of choice.

Control Center IndigoUltra® merges your choice of products, allowing a custom-tailored integrated system design. Performing reliably on any scale IndigoUltra® allows for quickest response times and accurate incident management.

With IndigoVision's Distributed Network Architecture, IndigoUltra® supports an unlimited number of client workstation installs and NVRs connected to the system; supporting continuous system growth whatever the future might bring.

Control Center is IndigoVision's effective, scalable and robust security management solution. It has an intuitive interface that provides easy system setup and efficient administration, saving you both time and money. Relentless testing and quality control 365 days per year ensures strong foundations for a robust, trusted security management offering.

IndigoUltra® delivers:

-  Unlimited Device Connections
-  Unlimited Client Workstations
-  Unlimited NVR Connections

## Product Codes

| Control Center   |           |
|--|-----------|
| IndigoVision Product CD/USB - Control Center Software                  | 340003    |
| IndigoUltra® Single Device Connection License                          | 340000-U  |
| IndigoPro® to IndigoUltra® - Upgrade Single Device Connection License  | 345000-PU |
| IndigoLite® to IndigoUltra® - Upgrade Single Device Connection License | 345000-LU |
| IndigoUltra® - Migration - Single Device Connection License            | 341000-U  |
| IndigoUltra® - Demo - Single Device Connection License                 | 346003-U  |

# Specifications

| General Specification   |  |   |  |
|---|--|---|--|
| Number of Device Connections                                    | Unlimited  | Connect to LPR powered by InnoWare <sup>5</sup> | Receive events/alarms, bookmarks and data records  |
| Number of Client Workstations                                   | Unlimited<br>(200 simultaneous connections per Site Database Server)   | Connect to BriefCam <sup>5</sup>                | ✓  |
| Number of NVR-AS Connections                                    | Unlimited  | FrontLine bodyworn devices integration          | Motorola VB300, VB400 <sup>7</sup>   |
| Live Video  | 100 video streams (25 per screen)  | Alarm and Bookmark Search                       | ✓  |
| GUI Themes  | Light Mode / Dark Mode   | Connect to CyberVigilant® <sup>5</sup>          | ✓  |
| Dynamic Profile Switching                                       | ✓  | Support for CyberVigilant® in Camera            | ✓  |
| PTZ Control   | ✓  | Integrated Data                                 | Manage millions of data records from LPR, EPOS and other integrations <sup>5</sup>   |
| Client-Side Dewarping   | ✓ <sup>4</sup>   | Alarm Escalation                                | ✓  |
| ONVIF PTZ Priority  | ✓  | Alarm Procedure Documents                       | HTML / Text / URL  |
| Audio   | Receive / Record / Transmit <sup>1</sup>   | System Alerts                                   | ✓  |
| Video Resolutions   | up to 20MP <sup>1</sup>  | Audit Log                                       | ✓  |
| Video Compression Formats                                       | MPEG-4 <sup>1</sup> / H.265 <sup>1</sup> / H.264 <sup>1</sup> / MJPEG <sup>1</sup> / JPEG2000 <sup>1</sup>                   | Mobile Client                                   | View live video and play back alarm video from ONVIF cameras, control PTZ cameras and manage alarms in web browser, Android or iOS app   |
| Video Compression Formats (Hardware Acceleration <sup>3</sup> ) | H.264 <sup>1</sup> / H.265 <sup>1</sup>  | Architecture                                    | DNA (Distributed Network Architecture)   |
| Audio Compression Formats                                       | Opus <sup>1</sup> / AAC <sup>1</sup> / G.711 <sup>1</sup>  | Segmented Databases                             | ✓  |
| Snapshots   | BMP / JPEG   | User Groups                                     | ✓  |
| Privacy Zones   | ✓  | Access Permissions                              | Object and function based permissions  |
| Sequences, Salvos and Guard Tours                               | ✓  | User Authentication                             | Windows Active Directory authentication / Basic password   |
| Pursuit Mode  | ✓  | PC Monitors                                     | 4  |
| Connect to Video Wall <sup>5</sup>                              | ✓  | Supported CCTV Keyboards                        | IndigoVision Surveillance Keyboard, Pelco KBD300A, Pelco CM9760-KBD, American Dynamics ADCC1100, American Dynamics AD2088, Panasonic WV-CU650 (Features may vary based on model)   |
| Playback  | 25 streams   | Multiple Languages                              | 10+ languages including; English, Chinese, French, German, Spanish   |
| Synchronised Playback   | ✓  | Matrix Numbering                                | 1 - 9,999,999  |
| Reverse Playback  | ✓  | Network Connection Types                        | TCP / UDP Unicast / UDP Multicast / HTTP / HTTPS <sup>6</sup>  |
| Thumbnail Overview  | Time / Alarm / Bookmark / Motion <sup>1</sup> / Audio <sup>1</sup>   | Device Discovery                                | ✓  |
| Incident Export   | Incident Player / 3rd Party Player (.mp4) <sup>1</sup>   | Supported Cameras and Encoders                  | IndigoVision Ultra, BX and GX camera ranges, 9000 Range Encoders, Camera Gateway <sup>2</sup> and ONVIF Profile S conformant 3rd party cameras   |
| Storyboard Export   | Export recordings from multiple cameras at different times, in any order   | Industry Open Standards                         | ONVIF Profile S  |
| Recording Schedules   | ✓  | License Mechanism                               | Software License Key. Federated License Server supported.  |
| Failover / Redundancy and Automatic NVR Switching               | ✓  | Control Center Supported OS                     | Windows 11*, Windows 10* 64-bit v1607 and later, Windows 8.1* 64-bit   |
| Security Overlays   | Overlay username on live and recorded video  | Windows NVR-AS Supported OS                     | Windows Server 2022*, Windows Server 2019*, Windows Server 2016*, Windows Server 2012 R2*, Windows Server 2012*, Windows 11*, Windows 10* 64-bit   |
| Watermarking  | Digital watermarking on recording and export   | License Server Supported OS                     | Windows Server 2022*, Windows Server 2019*, Windows Server 2016*, Windows Server 2012 R2*, Windows Server 2012*, Windows 11*, Windows 10* 64-bit. The License Server is also available as part of the IndigoVision NVR-AS 4000 Linux appliances. |
| Maps  | Multi-layered maps (BMP / JPEG / PNG / DWG), Tile Server   | Site Database Server Supported OS               | Windows Server 2022*, Windows Server 2019, Windows Server 2016, Windows Server 2012 R2, Windows 11*, Windows 10* 64-bit v1607 and later, Windows 8.1 64-bit  |
| Webpages  | ✓  |   |  |
| Zones   | Group multiple inputs into a single alarm  |   |  |
| Event Inputs  | Digital Input <sup>1</sup> / Analytics <sup>1</sup> / Network Loss / Video Loss <sup>1</sup> / Motion Detection <sup>1</sup> |   |  |
| Analytics Overlays  | ✓  |   |  |
| Third Party Inputs  | Through IndigoVision Integration Modules or IndigoVision Binding Kit   |   |  |
| Alarm Video   | Live and looped replay / Pre-alarm video / Alarm Groups  |   |  |
| Actions on Event  | Record / Email / Snapshot <sup>1</sup> / Move to Preset / Relay Output <sup>1</sup> / Audio <sup>1</sup>                     |   |  |
| Alarm Schedules   | ✓  |   |  |
| Alarm Reports   | ✓  |   |  |
| Bookmarking   | ✓  |   |  |
| Motion and Audio Search   | ✓  |   |  |

<sup>1</sup> Features may vary based on capabilities of the camera or encoder model. Please refer to the relevant product datasheets for details. <sup>2</sup> Please see our Camera Gateway Supported Cameras list for full details.

<sup>3</sup> For supported GPUs and resolutions, please refer to the Control Center Performance Reference Guide. <sup>4</sup> Supported cameras only. <sup>5</sup> Purchase product to be connected separately.

<sup>6</sup> HTTPS is only supported on new Control Center v16.1 or later installations. <sup>7</sup> Requires Motorola VideoManager license for any devices not originally purchased as an IndigoVision FrontLine or FrontLine 2 device.